

Digital To Analog Audio Converter

DEAR CUSTOMER

Thank you for purchasing this product. For optimum performance and safety, please read these instructions carefully before connecting, operating or adjusting this product. Please keep this manual for future reference.

FEATURES:

- Converts Coaxial or Toslink digital audio signals to analog L/R Audio
- Supports sampling rate at 32, 44.1, 48, and 96 KHz
- 24-bit S/PDIF incoming bit stream on left and right channels
- Provides electromagnetic noise free transmission
- Power Supply: 5V DC
- UL Listed

SPECIFICATIONS:

Input Audio	Coaxial or Toslink digital audio
Output Audio	L/R audio
Input audio connector	Toslink 1XRCA(Coaxial)
Output audio connector	2XRCA (R/L)
Sampling rate	32, 44.1, 48 and 96 KHz
Size(L-W-H)	1.625" W x 1" H x 2.5" D
Weight (Net)	78g
Limited Warranty.....	1 Year Parts and Labor
Operating Temperature.....	0 to +70 Degrees C
Operating Humidity	10% to 85 % RH (no condensation)
Storage Temperature	-10to +80 Degrees C
Storage Humidity	5% to 90 % RH (no condensation)
External Power Supply	5V DC@2A
Power Consumption	0.5 watts (max)
Converter Unit.....	FCC,CE,UL
Power Supply	UL,CE,FCC
AC Power Adapter	US standard

CONNECT AND OPERATE

Before installation, please make sure all devices you wish to connect have been turned off.

Connect the audio source device to the Converter using appropriate Toslink or Coaxial cables.

Connect the A/V Receivers or Amplifiers to the Converter using appropriate R/L cable.

Insert the DC side of 5v power supply into the converter and then connect the AC side of the power supply into the wall outlet.

Note: When connected to the Toslink and Coaxial cables at the same time, the product will give priority to Toslink input.

Attention: Insert / Extract cable gently.

PACKAGE CONTENTS

Before attempting to use this unit, please check the packaging and make sure the following items are contained in the shipping carton:

- Main unit (Digital to Analog Audio Converter)
- 5V DC Power Supply
- User's Manual

