



PULSEAUDIO™

6x6 Audio Distribution

AMPLIFIER



- 6 x 6 Audio Matrix with 6 Bridgeable zones to accommodate 1 or 2 speakers per zone
- Provides a Whole House Audio Control System - expandable up to 3 units for 18 Zones of distributed audio
- RS232-IP adapter and Android and IOS app allows for effortless control via smartphone or tablet
- Optional keypads with modern design fit seamlessly into any room. Keypads are POE with built-in IR Receivers (Keypads and 1 Cat5e/Cat6 Connection Hub sold separately as PA66ACCS)
- High efficiency Class D amplification
- Stereo/Bridge mono output
- Stereo/Bridge mode adjustable
- RS-232 port allows 2-way communication with 3rd party control systems
- Power 230V and 115V adjustable
- Ext. Mute & System on 3.5mm Mono Mini Phone Jacks
- 6 IR Emitter 3.5 mm Mono Mini Phone Jacks + 1 IR Emitter 3.5mm Mono for All Output Jack
- 1 PA Input Jack to set all Zone to Source 1
- 6 Zone Pre-AMP outputs to connect external power amplifier
- Accessory Kit (Part # PA66ACCS) sold separately

Part Number: PA66MK2



LEARN MORE AT VANCO1.COM