

120/240W 6-Channel Commercial Amplifiers

PA6X Sales Sheet



PA6X120 120W, 6-Channel Commercial Amplifier

120W of total power or 20W per channel



PA6X240 240W, 6-Channel Commercial Amplifier

240W of total power or 40W per channel

The PA6X series of 6-channel commercial amplifiers are designed for versatile audio distribution in retail, hospitality, and office environments. Supporting both 8ohm and 70/100V speaker systems, it offers flexible installation options to suit a wide range of projects. With inputs for two microphones, multiple line sources, Bluetooth connectivity, USB flash drives, SD/MMC memory cards, and a FM radio tuner, it delivers convenient playback and seamless mixing capabilities. Available with 120W or 240W total power output, these amplifiers provide reliable performance and a clear, balanced sound for any commercial setting.

Key features:

- Compatible with 4/8/16ohm and 70/100V speaker systems
- 120/240W total power or 20/40W per channel
- Multi-zone control to independently manage audio in 6 zones
- Front panel dials control for all functions
- Rack mounting ears and hardware included

Audio inputs:

- (2) 1/4" microphone inputs
- (3) Stereo RCA inputs
- (1) USB flash drive
- (1) SD/MMC memory card
- (1) FM radio tuner
- Bluetooth 5.0 connectivity

PA6X120 measurements:

Weight: 18lbs (8.2kg)

Dimensions (W x D x H): 19in x 15.2in x 3.5in (480mm x 385mm x 88mm)

PA6X240 measurements:

Weight: 21lbs (9.5kg)

Dimensions (W x D x H): 19in x 15.2in x 3.5in (480mm x 385mm x 88mm)

Box contents:

- (1) PA6X120/240 amplifier
- (1) Set of rack mounting ears and hardware
- (1) FM tuner antenna
- (1) Remote control
- (1) Quick start guide

Vanco International LLC provides a 2-year limited warranty for any defect in workmanship or materials under normal use from the date of purchase to the original owner. Please refer to the warranty page at www.vanco1.com for more details.

