



PULSEAUDIO™

6X6 AUDIO DISTRIBUTION AMPLIFIER



- 6x6 AUDIO MATRIX WITH BRIDGEABLE ZONES TO ACCOMMODATE 1 OR 2 SPECKERS PER ZONE
- PROVIDES A WHOLE HOUSE AUDIO CONTROL SYSTEM - EXPANDABLE UP TO 3 UNITS FOR 18 ZONES OF DISTRIBUTED AUDIO
- INTEGRATED WIFI ADAPTER WITH AVAILABLE ANDROID AND IOS APP THAT ALLOWS FOR CONTROL VIA SMARTPHONE OR TABLET
- OPTIONAL KEYPADS WITH MODERN DESIGN FITS SEAMLESSLY INTO ANY ROOM KEYPADS ARE POE WITH BUILT-IN IR RECEIVERS (KEYPADS AND 1 CAT5E/CAT6 CONNECTION HUB INCLUDED WITH PART #PA66KIT
- HIGH EFFICIENCY CLASS D AMPLIFICATION
- STEREO/BRIDGE MONO OUTPUT
- STEREO/BRIDGE MODE ADJUSTABLE
- IR REMOTE CONTROLLER FOR SOURCE SELECTION/VOLUME/TREBLE/BASS
- RS-232 PORT ALLOWS 2 WAY COMMUNICATION WITH THE HOME AUTOMATION
- POWER 230V AND 115V ADJUSTABLE
- EXT. MUTE & SYSTEM ON 3.5MM MONO MINI PHONE JACKS
- 6 IR EMITTER 3.5 MM MONO MINI PHONE JACKS + 1 IR EMITTER 3.5 MM MONO FOR ALL OUTPUT JACK
- 1 PA INPUT JACK TO SEE ALL ZONE TO SOURCE 1
- 3 ZONE PRE-AMP OUTPUTS TO CONNECT EXTERNAL POWER AMPLIFY
- INTEGRATE AND CONTROL YOUR STREAMING SERVICES WITH PULSEAUDIO'S PASTREAM INTEGRATED AUDIO SOURCE STREAMER OR CASATUNES MULTI-ROOM, MULTI-MODE MUSIC SERVICES (SOLD SEPARATELY)



**PART NUMBER:
PA66AMP and PA66KIT**

Pulseaudio1.com