



# 8x7 HDBaseT™ Matrix Selector Switch with Additional HDMI® Output



**Quick Install Kit includes  
7 HDBaseT PoC Receivers  
and IR accessories!**

- HDBaseT Matrix that features 7 HDBaseT outputs and 1 HDMI output
- Quick install kit includes 7 HDBaseT PoC receivers, 8 IR Emitter and Receiver sets and IR remote control
- Supports HDCP 2.2, and is backwards compatible with previous version of HDCP and HDMI
- Transmits 4Kx2K@ 60Hz 4:2:0 up to 26 ft (8m) via HDMI port and 131 ft (40m) via HDBaseT port
- 7 HDBaseT outputs with distances up to 230 ft (70m) at 1080p and 131 ft (40m) at 4Kx2K on a single Cat5e/6 cable
- HDBaseT Receivers are powered by the matrix using PoC technology
- LED indicators show real-time switching status
- Controllable via front panel, RS232, IR and TCP/IP
- Supports bi-directional IR & RS232 control
- Built-in GUI for TCP/IP control and setup
- Powerful EDID management
- Features Micro USB port for firmware upgrades
- Easy installation with rack-mounting design, mounting hardware included
- Power Supply: Matrix Unit, AC100-240V; Receivers, PoC
- Matrix Dimensions: 17.2" W x 1.7" H x 11.8" D
- Receiver Dimensions: 2.4" W x .9" H x 4.7" D

**Part Number: HDBT8X7**

**vanco1.com**